

## 120W DIGITIAL MIXER AMPLIFIER 100V $4\Omega$

## **MA-13MK2**







Rated output power	120W
Tone adjustment	Bass: ±10dB(at 100Hz),Treble: ±10dB(at 10Hz)
Output mode	$4\text{-}6\Omega$ constant resistance output, $70\text{V}/100\text{V}$ constant pressure output
Auxiliary output	600Ω 1V(0dBV)
Input	Microphone 1,2,3,600Ω/2mV-4mV,AUX1.2,10kΩ/200mV, unbalanced
Frequency response	20Hz-20KHz
Total harmonic distortion	<0.3%
Signal to noise ratio	85dB
Safeguard	AC fuse, over current, overload, short circuit voice prompt
Mute control	Microphone 1 input signal overrides other input signals
Power source	AC 220V±10% 50Hz

- ♦ Combined multifunctional integrated-amplifier with FM+USB+MMC+Bluetooth+Remote
- ◆Plug-Play USB disk,with FM radio,wireless remote control,
- ◆3\*Microphone inputs,2\*auxiliary inputs,and 1\*auxiliary outputs for link,
- ◆Transformer Isolated 70-100V and 4-16 Ohms speakers output,
- ◆Compatible with muting function,
- ◆Individual volume control,low and high tone control,
- ◆Protection for short-C,over-hot,over-load and alarm function,
- ◆Standard.specification:120W,
- ◆Panel Material: High class aluminum; Using advenced polishing process
- ♦ Shell Material: Iron; Surface Treatment: Sandblasted black